

VARIADORES DE VELOCIDAD - Ventiladores & Bombas*

230V, 3 Fases, 50/60Hz

REFERENCIA	HP	KW	Salida Nominal (A)	Sobrecarga 1min (A)
6KFP23001X9XXXA1	1	1,1	4,6	5,1
6KFP23002X9XXXA1	2	1,5	7,5	8,3
6KFP23003X9XXXA1	3	2,2	10,6	11,7
6KFP23005X9XXXA1	5	3,7	16,7	18,4
6KFP23007X9XXXA1	7,5	5,5	24,2	26,6
6KFP23010X9XXXA1	10	7,5	30,8	33,9
6KFP23015X9XXXA1	15	11	46,2	50,8
6KFP23020X9XXXA1	20	15	59,4	65,3
6KFP23025X9XXXA1	25	18,5	74,8	82,3
6KFP23030X9XXXA1	30	22	88	96,8
6KFP23040X9XXXA1	40	30	115	126,5
6KFP23050X9XXXA1	50	37	143	157
6KFP23060X9XXXA1	60	45	170	187,0

460V, 3 Fases, 50/60Hz

REFERENCIA	HP	KW	Salida Nominal (A)	Sobrecarga 1min (A)
6KFP43001X9XXXA1	1	1,1	2,1	2,31
6KFP43002X9XXXA1	2	1,5	3,4	3,74
6KFP43003X9XXXA1	3	2,2	4,8	5,28
6KFP43005X9XXXA1	5	3,7	8,2	9
6KFP43007X9XXXA1	7,5	5,5	11	12
6KFP43010X9XXXA1	10	7,5	14,5	16
6KFP43015X9XXXA1	15	11	21	23
6KFP43020X9XXXA1	20	15	27	30
6KFP43025X9XXXA1	25	18,5	34	37,4
6KFP43030X9XXXA1	30	22	40	44
6KFP43040X9XXXA1	40	30	52	57,2
6KFP43050X9XXXA1	50	37	65	71,5
6KFP43060X9XXXA1	60	45	80	88
6KFP43075X9XXXA1	75	55	105	115,5
6KFP43100X9XXXA1	100	75	130	143
6KFP43125X9XXXA1	125	90	160	176

460V, 3 Fases, 50/60Hz (cont.)

REFERENCIA	HP	KW	Salida Nominal (A)	Sobrecarga 1min (A)
6KFP43150X8XXXA1	150	110	190	209
6KFP43200X8XXXA1	200	132	240	264
6KFP43250X8XXXA1	250	160	302	332
6KFP43300X8XXXA1	300	200	361	397
6KFP43350X8XXCA1	350	250	443	487
6KFP43450X8XXCA1	450	298	540	594
6KFP43500X8XXCA1	500	355	590	649
6KFP43550X8XXCA1	550	400	678	746
6KFP43600X8XXCA1	600	450	730	803
6KFP43650X1XXCA1	650	500	780	858
6KFP43750X1XXCA1	750	560	890	979
6KFP43900X1XXCA1	900	630	1050	1155
6KFP431K0X1XXCA1	1000	710	1160	1276
6KFP431K2X1XXCA1	1200	800	1380	1518
6KFP431K3X1XXCA1	1350	1000	1530	1683

